

## Claims

- Sub  
a1
1. A method of operating a telecommunications system comprising the steps of:  
transmitting substantially simultaneously over separate first and second  
telecommunication channels a first and a second forward error correction coded signal,  
respectively, each of the first and second signals nominally containing the same user  
information and the first and second signals being digital signals;  
forward error correction coding at least a portion of the first signal; and  
forward error correction coding at least a portion of the second signal;  
characterised in that the forward error correction coding of the first and second  
signals includes the step of puncturing and the bits which are punctured from the portion  
of the first signal are different from the bits punctured from the portion of the second  
signal.
2. The method according to claim 2, characterised in that the forward error correction  
coding of the first and second signals includes convolutional or turbo coding.
3. The method according to claim 1 or 2, further characterised by the steps of:  
receiving the forward error correction coded first and second signals; and  
decoding the first and second forward error correction coded signals to obtain the user  
information.
4. The method according to claims 3, characterised in that the decoding step is preceded  
by a depuncturing step.
5. The method according to claim 3 or 4, characterised in that the decoding step includes  
one of:  
depuncturing each of the first and second forward error correction coded signals  
separately, combining the first and second depunctured signals and then decoding the  
combined signal;  
depuncturing each of the first and second forward error correction coded signals  
separately and then decoding and combining the first and second signals simultaneously  
in a multi-input decoder;

Sub  
a1

depuncturing each of the first and second forward error correction coded signals separately, soft decoding each of the first and second depunctured coded signals separately, and then selecting on a bit-by-bit basis from the first and second soft decoded signals.

5

6. A method of operating a receiver in a telecommunications system, comprising the steps of:

receiving a first forward error correction coded first signal;

receiving a second forward error correction coded second signal substantially

10 simultaneously with the first signal, each of the first and second signals having a different forward error correction coding, each of the first and second signals being decodable to recover substantially the same uncoded user message and the first and second signals being digital signals; and

15 decoding the first and second received signals to obtain the user message, characterised in that and the forward error correction decoding of the first and second signals includes the step of de-puncturing and the bits which are punctured from the first signal are different from the bits punctured from the second signal.

20 7. The method according to claim 6, characterised in that the forward error correction coding of the first and second signals includes convolutional or turbo coding.

8. The method according to claims 6 or 7, characterised in that the decoding step is preceded by the depuncturing step.

25 9. The method according to claim 6 or 7, characterised in that the decoding step includes one of:

depuncturing each of the first and second forward error correction coded signals separately, combining the first and second depunctured signals and then decoding the combined signal;

30 depuncturing each of the first and second forward error correction coded signals separately and then decoding and combining the first and second signals simultaneously in a multi-input decoder;

depuncturing each of the first and second forward error correction coded signals

Sub  
a1

separately, soft decoding each of the first and second depunctured coded signals separately, and then selecting on a bit-by-bit basis from the first and second soft decoded signals.

5 10. A transmitter system comprising one or more transmitters, the one or more transmitters comprising one or more forward error correction coders; wherein the one or more transmitters and the one or more forward error correction coders are adapted to transmit, substantially simultaneously over separate first and second telecommunication channels, respectively a first and a second forward error correction coded signal, the first and second signals being digital signals, each signal nominally containing the same user information, characterised in that the forward error correction coder includes a puncturing unit and the puncturing unit is adapted so that the bits which are punctured from the first signal are different from the bits punctured from the second signal.

15 11. A telecommunications system comprising:  
one or more transmitters and one or more receivers; the one or more transmitters including one or more forward error correction coders; wherein the one or more transmitters and the one or more forward error correction coders are adapted to transmit, substantially simultaneously over separate first and second telecommunication channels, respectively a first and a second forward error correction coded signal, the first and second signals being digital signals, each signal nominally containing the same user information, characterised in that the forward error correction coder includes a puncturing unit and the puncturing unit is adapted so that the bits which are punctured from the first signal are different from the bits punctured from the second signal.

25 12. The telecommunications system according to claim 11, further characterised by:  
one or more receivers comprising:  
a forward error correction decoder for substantially simultaneously decoding the first forward error correction coded signal and the second forward error correction coded signal, each of the first and second signals being decodable to recover the same uncoded user message, the first and second signals being digital signals and the forward error correction decoder including a de-puncturing unit, the de-puncturing unit being adapted so that the bits which are de-punctured from the first signal are different from the bits de-

Sub  
al

punctured from the second signal.

13. A telecommunications receiver system, comprising:  
one or more receivers comprising:

5 a forward error correction decoder for substantially simultaneously decoding a first forward error correction coded signal and a second forward error correction coded signal, each of the first and second signals being decodable to recover the same uncoded user message, the first and second signals being digital signals, characterised in that the forward error correction decoder including a de-puncturing unit, the de-puncturing unit  
10 being adapted so that the bits which are de-punctured from the first signal are different from the bits de-punctured from the second signal.

14. The system according to any of the claims 10 to 13, characterised in that the forward error correction coding of the first and second signals includes convolutional or turbo  
15 coding.

15. The system according to any of the claims 12 to 14, characterised in that the de-puncturing unit and the decoder are adapted for one of the following:  
the depuncturing unit depunctures each of the first and second forward error correction  
20 coded signals separately and the decoder decodes each of the depunctured signals separately;  
the depuncturing unit depunctures each of the first and second forward error correction coded signals separately, and the decoder comprises a combiner which combines the first and second depunctured signals and subsequently the decoder decodes the combined  
25 signal;  
the decoder is a multi-input decoder, the depuncturing unit depunctures each of the first and second forward error correction coded signals separately and then the decoder decodes and combines the first and second signals simultaneously;  
the decoder includes a soft decoder and a combiner, the depuncturing unit depunctures  
30 each of the first and second forward error correction coded signals separately, the decoder soft decodes each of the first and second depunctured coded signals separately, and then the combiner combines the decoded first and second signals by selecting on a bit-by-bit basis from the first and second soft decoded signals in a selector.

Sub  
al

16. The method according to any of the claims 1 to 9, characterised in that the telecommunications system is a mobile radio telecommunications system.
- 5 17. The method according to any of the claims 1 to 9, or 16, characterised in that the first and second forward error correction coded signals are spread spectrum signals.
18. The method according to any of the claims 1 to 9, 16 or 17 characterised in that the telecommunications system is a code division multiple access system.
- 10 19. The system according to any of the claims 10 to 15, characterised in that the telecommunications system is a mobile radio telecommunications system.
- 15 20. The system according to any of the claims 10 to 15, or 19, characterised in that the first and second forward error correction coded signals are spread spectrum signals.
21. The system according to any of the claims 10 to 15, 19 or 20 characterised in that the telecommunications system is a code division multiple access system.
- 20 22. A mobile radio terminal comprising the receiver system of any of the claims 13 to 15, or 19 to 21.
23. A mobile radio terminal comprising the transmitter system of claim 10.
- 25 24. A forward correction coder adapted to transmit a first and a second forward error correction coded signal, each signal nominally containing the same user information, substantially simultaneously over separate first and second telecommunication channels, respectively, the first and second signals being digital signals characterised in that the forward error correction coder includes a puncturing unit and the puncturing unit is
- 30 adapted so that the bits which are punctured from the first signal are different from the bits punctured from the second signal.
25. A forward error correction decoder, for substantially simultaneously decoding a first

6

Sub  
at

forward error correction coded signal and a second forward error correction coded signal, the first and second forward error correction coded signals being digital signals and each of the first and second signals being decodable to recover the same uncoded user message, characterised in that the forward error correction decoder includes a de-puncturing unit, the de-puncturing unit being adapted so that the bits which are de-punctured from the first signal are different from the bits de-punctured from the second signal.

5

add  
at